(54) Title: PLASMA REACTOR WITH OVERHEAD RF ELECTRODE TUNED TO THE PLASMA

(57) Abstract: In accordance with one aspect of the invention, a plasma reactor has a capacitive electrode driven by an RF power source, and the electrode capacitance is matched at the desired plasma density and RF source frequency to the negative capacitance of the plasma, to provide an electrode plasma resonance supportive of a broad process window within which the plasma may be sustained.

PLASMA REACTOR WITH OVERHEAD RF ELECTRODE
TUNED TO THE PLASMA

BACKGROUND OF THE INVENTION

5   An RF plasma reactor is used to process semiconductor
wafers to produce microelectronic circuits. The reactor
forms a plasma within a chamber containing the wafer to be
processed. The plasma is formed and maintained by
application of RF plasma source power coupled either
10   inductively or capacitively into the chamber. For
capacitive coupling of RF source power into the chamber, an
overhead electrode (facing the wafer) is powered by an RF
source power generator.

       One problem in such reactors is that the output
15   impedance of the RF generator, typically 50 Ohms, must be
matched to the load impedance presented by the combination
of the electrode and the plasma. Otherwise the amount of
RF power delivered to the plasma chamber will fluctuate
with fluctuations in the plasma load impedance so that
20   certain process parameters such as plasma density cannot be
held within the required limits. The plasma load impedance
fluctuates during processing because it depends upon
conditions inside the reactor chamber which tend to change
dynamically as processing progresses. At an optimum plasma
25   density for dielectric or metal etch processes, the load
impedance is very small compared to the output impedance of
the RF generator and can vary significantly during the
processing of the wafer. Accordingly, an impedance match
circuit must be employed to actively maintain an impedance
30   match between the generator and the load. Such active
impedance matching uses either a variable reactance and/or
a variable frequency. One problem with such impedance
match circuits is that they must be sufficiently agile to
follow rapid changes in the plasma load impedance, and

1

therefore are relatively expensive and can reduce system
reliability due to their complexity.

Another problem is that the range of load impedances
over which the match circuit can provide an impedance match

5   (the "match space") is limited. The match space is related
to the system Q, where $Q = \Delta f/f$, f being a resonant
frequency of the system and Δf being the bandwidth on
either side of f within which resonant amplitude is within
6 dB of the peak resonant amplitude at f. The typical RF

10 generator has a limited ability to maintain the forward
power at a nearly constant level even as more RF power is
reflected back to the generator as the plasma impedance
fluctuates. Typically, this is achieved by the generator
servoing its forward power level, so that as an impedance

15 mismatch increases (and therefore reflected power
increases), the generator increases its forward power
level. Of course, this ability is limited by the maximum
forward power of which the generator is capable of
producing. Typically, the generator is capable of

20 handling a maximum ratio of forward standing wave voltage
to reflected wave voltage (i.e., the voltage standing wave
ratio or VSWR) of not more than 3:1. If the difference in
impedances increases (e.g., due to plasma impedance
fluctuations during processing) so that the VSWR exceeds

25 3:1, then the RF generator can no longer control the
delivered power, and control over the plasma is lost. As
a result, the process is likely to fail. Therefore, at
least an approximate impedance match must be maintained
between the RF generator and the load presented to it by

30 the combination of the coil antenna and the chamber. This
approximate impedance match must be sufficient to keep the
VSWR at the generator output within the 3:1 VSWR limit
over the entire anticipated range of plasma impedance
fluctuations. The impedance match space is, typically,

35 the range of load impedances for which the match circuit

2

can maintain the VSWR at the generator output at or below 3:1.

A related problem is that the load impedance itself is highly sensitive to process parameters such as chamber
5   pressure, source power level, source power frequency and plasma density. This limits the range of such process parameters (the "process window") within which the plasma reactor must be operated to avoid an unacceptable impedance mismatch or avoid fluctuations that take load impedance
10   outside of the match space. Likewise, it is difficult to provide a reactor which can be operated outside of a relatively narrow process window and use, or one that can handle many applications.

Another related problem is that the load impedance is
15   also affected by the configuration of the reactor itself, such as dimensions of certain mechanical features and the conductivity or dielectric constant of certain materials within the reactor. (Such configurational items affect reactor electrical characteristics, such as stray
20   capacitance for example, that in turn affect the load impedance.) This makes it difficult to maintain uniformity among different reactors of the same design due to manufacturing tolerances and variations in materials. As a result, with a high system Q and correspondingly small
25   impedance match space, it is difficult to produce any two reactors of the same design which exhibit the same process window or provide the same performance.

Another problem is inefficient use of the RF power source. Plasma reactors are known to be inefficient, in
30   that the amount of power delivered to the plasma tends to be significantly less than the power produced by the RF generator. As a result, an additional cost in generator capability and a trade-off against reliability must be incurred to produce power in excess of what is actually
35   required to be delivered into the plasma.

3

SUMMARY OF THE INVENTION

In accordance with one aspect of the invention, a
plasma reactor has a capacitive electrode driven by an RF
5   power source, and the electrode capacitance is matched at
the desired plasma density and RF source frequency to the
negative capacitance of the plasma, to provide an electrode
plasma resonance and a broad process window within which
the plasma may be sustained.   It is a discovery of the
10 invention that selecting a VHF frequency for the RF power
source enables the foregoing match to be implemented at
plasma densities which favor certain plasma processes such
as etch processes.

In accordance with another aspect of the invention, an
15 RF source is impedance-matched to the electrode-plasma load
impedance through a tuning stub connected at one end to the
electrode.   The stub has a length providing a resonance at
or near the frequency of the RF source and/or the resonant
frequency of the electrode-plasma combination.   The RF
20 generator is tapped to the stub at or near a location along
the stub at which the input impedance matches the RF source
impedance.

In a preferred embodiment, the process window is
further expanded by slightly offsetting the electrode-
25 plasma resonant frequency, the stub resonant frequency and
the RF source frequency from one another.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a cut-away cross-sectional side view of a
30 plasma reactor embodying the present invention.

FIGS. 2A and 2B are diagrams illustrating,
respectively, the coaxial stub of FIG. 1 and the voltage
and current standing wave amplitudes as a function of
position along the coaxial stub.

4

FIG. 3 illustrates the subtraction of current at the input power tap point on the coaxial stub that occurs in response to high plasma load impedance in a preferred embodiment to maintain a more constant delivered VHF power

5   level in a larger match space.

FIG. 4 illustrates the addition of current at the input power tap point on the coaxial stub that occurs in response to low plasma load impedance in a preferred embodiment to maintain a more constant delivered VHF power

10   level in a larger match space.

FIG. 5 is a graph illustrating the low-Q reflection coefficient as a function of frequency of the embodiment of FIG. 1.

FIG. 6 is a graph illustrating the interaction of the

15   current contribution at the input power tap point on the coaxial stub with the standing wave current and voltage along the stub length.

FIG. 7 illustrates an alternative embodiment of the coaxial stub of FIG. 1.

20

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiment Overview:

Referring to FIG. 1, a plasma reactor includes a reactor chamber 100 with a wafer support 105 at the bottom

25   of the chamber supporting a semiconductor wafer 110. A semiconductor ring 115 surrounds the wafer 110. The semiconductor ring 115 is supported on the grounded chamber body 127 by a dielectric (quartz) ring 120. In the preferred embodiment, this is of a thickness of 10 mm and

30   dielectric constant of 4. The chamber 100 is bounded at the top by a disc shaped overhead aluminum electrode supported at a predetermined gap length above the wafer 110 on grounded chamber body 127 by a dielectric (quartz) seal. The overhead electrode 125 also may be a metal

35   (e.g., aluminum) which may be covered with a semi-metal

5

material (e.g., Si or SiC) on its interior surface, or it
may be itself a semi-metal material. An RF generator 150
applies RF power to the electrode 125. RF power from the
generator 150 is coupled through a coaxial cable 162

5   matched to the generator 150 and into a coaxial stub 135
connected to the electrode 125. The stub 135 has a
characteristic impedance, resonance frequency, and provides
an impedance match between the electrode 125 and the
coaxial cable 162/RF power generator 150, as will be more

10 fully described below. The chamber body is connected to
the RF return (RF ground) of the RF generator 150. The RF
path from the overhead electrode 125 to RF ground is
affected by the capacitance of the semiconductor ring 115,
the dielectric ring 120 and the dielectric seal 130 . The

15 wafer support 105, the wafer 110 and the semiconductor ring
115 provide the primary RF return path for RF power applied
to the electrode 125.

     The capacitance of the overhead electrode assembly
126, including the electrode 125, the dielectric ring 120

20 and dielectric seal 130 measured with respect to RF return
or ground is, in the preferred embodiment, preferably 180
pico farads. The electrode assembly capacitance is
affected by the electrode area, the gap length (distance
between wafer support and overhead electrode), and by

25 factors affecting stray capacitances, especially the
dielectric values of the seal 130 and of the dielectric
ring 120, which in turn are affected by the dielectric
constants and thicknesses of the materials employed. More
generally in the preferred embodiment, the capacitance of

30 the electrode assembly (an unsigned number or scalar) is
equal or nearly equal in magnitude to the negative
capacitance of the plasma (a complex number) at a
particular source power frequency, plasma density and
operating pressure, as will be discussed below.

6

Many of the factors influencing the foregoing
relationship are in great part predetermined due to the
realities of the plasma process requirements needed to be
performed by the reactor, the size of the wafer, and the
5 requirement that the processing be carried out uniformly
over the wafer. Thus, the plasma capacitance is a function
of the plasma density and the source power frequency, while
the electrode capacitance is a function of the wafer
support-to-electrode gap (height), electrode diameter, and
10 dielectric values of the insulators of the assembly.
Plasma density, operating pressure, gap, and electrode
diameter must satisfy the requirements of the plasma
process to be performed by the reactor. In particular, the
ion density must be within a certain range. For example,
15 silicon and dielectric plasma etch processes generally
require the plasma ion density to be within the range of 10^9
- 10^{12} ions/cc. The wafer electrode gap provides an optimum
plasma ion distribution uniformity for 8 inch wafers, for
example, if the gap is about 2 inches. The electrode
20 diameter is preferably at least as great as, if not greater
than the diameter of the wafer. Operating pressures
similarly have practically preferred ranges for typical
etch and other plasma processes.

But it has been found that other factors remain which
25 can be selected to achieve the above preferred
relationship, particularly choice of source frequency and
choice of capacitances for the overhead electrode assembly
126. Within the foregoing dimensional constraints imposed
on the electrode and the constraints (e.g., density range)
30 imposed on the plasma, the electrode capacitance can be
matched to the magnitude of the negative capacitance of the
plasma if the source power frequency is selected to be a
VHF frequency, and if the dielectric values of the
insulator components of electrode assembly 126 are selected
35 properly. Such selection can achieve a match or near match

7

between source power frequency and plasma-electrode
resonance frequency.

Accordingly in one aspect of the preferred embodiment,
for an 8-inch wafer the overhead electrode diameter is
5   approximately 11 inches, the gap is about 2 inches, the
plasma density and operating pressure is typical for etch
processes as above-stated, the dielectric material for the
seal 130 has a dielectric constant of 9 and a thickness of
the order of 1 inch, the ring 115 has an inner diameter of
10 slightly in excess of 10 inches and an outer diameter of
about 13 inches, the ring 120 has a dielectric constant of
4 and a thickness of the order of 10mm, the VHF source
power frequency is 210 MHz (although other VHF frequencies
could be equally effective), and the source power
15 frequency, the plasma electrode resonance frequency and the
stub resonance frequency are all matched or nearly matched.

More particularly, in the preferred embodiment these
three frequencies are slightly offset from one another,
with the source power frequency being 210 MHz, the
20 electrode-plasma resonant frequency being approximately 200
MHz, and the stub frequency being about 220 MHz, in order
to achieve a de-tuning effect which advantageously reduces
the system Q. Such a reduction in system Q renders the
reactor performance less susceptible to changes in
25 conditions inside the chamber, so that the entire process
is much more stable and can be carried out over a far wider
process window.

The coaxial stub 135 is a specially configured design
which further contributes to the overall system stability,
30 its wide process window capabilities, as well as many other
valuable advantages. It includes an inner cylindrical
conductor 140 and an outer concentric cylindrical conductor
145. An insulator 147 (denoted by cross-hatching in FIG. 1)
preferably having a relative dielectric constant of 1 fills
35 the space between the inner and outer conductors 140, 145.

8

The inner and outer conductors 140, 145 are formed of
nickel-coated aluminum. In the preferred embodiment, the
outer conductor 145 preferably has a diameter of about 4.32
inches and the inner conductor 140 preferably has a

5   diameter of about 1.5 inches. The stub characteristic
impedance is determined by the radii of the inner and outer
conductors 140, 145 and the dielectric constant of the
insulator 147. The stub 135 of the preferred embodiment
described above has a characteristic impedance of 65 Ω.

10 More generally, the stub characteristic impedance exceeds
the source power output impedance by about 20%-40% and
preferably by about 30%. The stub 135 has an axial length
of about 29 inches --a quarter wavelength at 220 MHz--in
order to have a resonance in the vicinity of 220 MHz to

15 generally match while being slightly offset from the
preferred VHF source power frequency of 210 MHz.

A tap 160 is provided at a particular point along the
axial length of the stub 135 for applying RF power from the
RF generator 150 to the stub 135, as will be discussed

20 below. The RF power terminal 150a and the RF return
terminal 150b of the generator 150 are connected at the tap
160 on the stub 135 to the inner and outer coaxial stub
conductors 140, 145, respectively. These connections are
made via a generator-to-stub coaxial cable 162 having a

25 characteristic impedance that matches the output impedance
of the generator 150 (typically, 50 Ω) in the well-known
manner. A terminating conductor 165 at the far end 135a of
the stub 135 shorts the inner and outer conductors 140, 145
together, so that the stub 135 is shorted at its far end

30 135a. At the near end 135b (the unshorted end) of the stub
135, the outer conductor 145 is connected to the chamber
body via an annular conductive housing or support 175,
while the inner conductor 140 is connected to the center of
electrode 125 via a conductive cylinder or support 176.

35 Preferably, a dielectric ring 180, which in the preferred

9

embodiment has a thickness of 1.3 inch and dielectric constant 9, is held between and separates the conductive cylinder 176 and the electrode 125.

5   Preferably, the inner conductor 140 provides a conduit for utilities such as process gases and coolant. The principal advantage of this feature is that, unlike typical plasma reactors, the gas line 170 and the coolant line 173 do not cross large electrical potential differences. They therefore may be constructed of metal, a less expensive and 10 more reliable material for such a purpose. The metallic gas line 170 feeds gas inlets 172 in or adjacent the overhead electrode 125 while the metallic coolant line 173 feeds coolant passages or jackets 174 within the overhead electrode 125.

15   An active and resonant impedance transformation is thereby provided by this specially configured stub match between the RF generator 150, and the overhead electrode assembly 126 and processing plasma load, minimizing reflected power and providing a very wide impedance match 20 space accomodating wide changes in load impedance. Consequently, wide process windows and process flexibility is provided, along with previously unobtainable efficiency in use of power, all while minimizing or avoiding the need for typical impedance match apparatus. As noted above, the 25 stub resonance frequency is also offset from ideal match to further enhance overall system Q, system stability and process windows and multi-process capability.

Matching the Electrode-Plasma Resonance Frequency and the 30 VHF Source Power Frequency:
       As outlined above, a principal feature is to configure the overhead electrode assembly 126 for resonance with the plasma at the electrode-plasma resonant frequency and for the matching (or the near match of) the source power 35 frequency and the electrode-plasma frequency. The

10

electrode assembly 126 has a predominantly capacitive
reactance while the plasma reactance is a complex function
of frequency, plasma density and other parameters. (As
will be described below in greater detail, a plasma is
5 analyzed in terms of a reactance which is a complex
function involving imaginary terms and generally
corresponds to a negative capacitance.) The electrode-
plasma resonant frequency is determined by the reactances
of the electrode assembly 126 and of the plasma (in analogy
10 with the resonant frequency of a capacitor/inductor
resonant circuit being determined by the reactances of the
capacitor and the inductor). Thus the electrode-plasma
resonant frequency may not necessarily be the source power
frequency, depending as it does upon the plasma density.
15 The problem, therefore, in carrying out the preferred
embodiment of the invention, is to find a source power
frequency at which the plasma reactance is such that the
electrode-plasma resonant frequency is equal or nearly
equal to the source power frequency, given the constraints
20 of practical confinement to a particular range of plasma
density and electrode dimensions. The problem is even more
difficult, because the plasma density (which affects the
plasma reactance) and the electrode dimensions (which
affect electrode capacitance) must meet certain process
25 constraints. Specifically, for dielectric and metal plasma
etch processes, the plasma density should be within the
range of 10^9-10^{12} ions/cc, which is a constraint on the
plasma reactance. Moreover, a more uniform plasma ion
density distribution for processing 8-inch diameter wafers
30 for example, is realized by a wafer-to-electrode gap or
height of about 2 inches and an electrode diameter on the
order of the wafer diameter, or greater, which is a
constraint on the electrode capacitance.

Accordingly in one feature of the preferred
35 embodiment, by matching (or nearly matching) the electrode

11

capacitance to the magnitude of the negative capacitance of
the plasma, the electrode-plasma resonant frequency and the
source power frequency are at least nearly matched. For
the general metal and dielectric etch process conditions

5   enumerated above (i.e., plasma density between 10^9-10^{12}
ions/cc, a 2-inch gap and an electrode diameter on the
order of roughly 11 inches), the match is possible if the
source power frequency is a VHF frequency. Other
conditions (e.g., different wafer diameters, different

10 plasma densities, etc.) may dictate a different frequency
range to realize such a match in carrying out this feature
of the invention. As will be detailed below, under favored
plasma processing conditions for processing 8-inch wafers
in several principal applications including dielectric and

15 metal plasma etching and chemical vapor deposition, the
plasma capacitance in one typical working example of the
preferred embodiment having plasma densities as set forth
above was between -50 and -400 pico farads. In the
preferred embodiment the capacitance of the overhead

20 electrode assembly 126 was matched to the magnitude of
this negative plasma capacitance by using an electrode
diameter of 11 inches, a gap length (electrode to pedestal
spacing) of approximately 2 inches, choosing a dielectric
material for seal 130 having a dielectric constant of 9,

25 and a thickness of the order of one inch, and a dielectric
material for the ring 120 having a dielectric constant of
4 and thickness of the order of 10 mm.

The combination of electrode assembly 126 and the
plasma resonates at an electrode-plasma resonant frequency

30 that at least nearly matches the source power frequency
applied to the electrode 125, assuming a matching of their
capacitances as just described. We have discovered that
for favored etch plasma processing recipes, environments
and plasmas, this electrode-plasma resonant frequency and

35 the source power frequency can be matched or nearly

12

matched at VHF frequencies; and that it is highly
advantageous that such a frequency match or near-match be
implemented.   In the preferred embodiment, the electrode-
plasma resonance frequency corresponding to the foregoing

5   values of plasma negative capacitance is approximately 200
MHz, as will be detailed below. The source power
frequency is 210 MHz, a near-match in which the source
power frequency is offset slightly above the electrode-
plasma resonance frequency in order to realize other

10   advantages to be discussed below.
       The plasma capacitance is a function of among other
things, plasma electron density. This is related to
plasma ion density, which needs, in order to provide good
plasma processing conditions, to be kept in a range

15   generally 10^9 to 10^{12} ions/cc. This density, together with
the source power frequency and other parameters,
determines the plasma negative capacitance, the selection
of which is therefore constrained by the need to optimize
plasma processing conditions, as will be further detailed.

20   below. But the overhead electrode assembly capacitance is
affected by many physical factors, e.g. gap length
(spacing between electrode 125 and the wafer); the area of
electrode 125; the choice of dielectric constant of the
dielectric seal 130 between electrode 125 and grounded

25   chamber body 127; the choice of dielectric constant for
the dielectric ring 120 between semiconductor ring 115 and
the chamber body; and the thickness of the dielectric
structures of seal 130 and ring 120 and the thickness and
dielectric constant of the ring 180. This permits some

30   adjustment of the electrode assembly capacitance through
choices made among these and other physical factors
affecting the overhead electrode capacitance. We have
found that the range of this adjustment is sufficient to
achieve the necessary degree of matching of the overhead

35   electrode assembly capacitance to the magnitude of the

13.

negative plasma capacitance. In particular, the dielectric materials and dimensions for the seal 130 and ring 120 are chosen to provide the desired dielectric constants and resulting dielectric values. Matching the

5   electrode capacitance and the plasma capacitance can then be achieved despite the fact that some of the same physical factors influencing electrode capacitance, particularly gap length, will be dictated or limited by the following practicalities: the need to handle larger

10 diameter wafers; to do so with good uniformity of distribution of plasma ion density over the full diameter of the wafer; and to have good control of ion density vs ion energy.

Accordingly in the preferred embodiment, for plasma

15 ion density ranges as set forth above favorable to plasma etch processes; and for chamber dimensions suitable for processing 8 inch wafers, a capacitance for electrode assembly 126 was achieved which matched the plasma capacitance of -50 to -400 pico farads by using an

20 electrode diameter of 11 inches, a gap length of approximately 2 inches, and a material for the seal 130 having a dielectric constant of 9, and a material for the ring 120 having a dielectric constant of 4.

Given the foregoing range for the plasma capacitance

25 and the matching overhead electrode capacitance, the electrode-plasma resonance frequency was approximately 200 MHz for a source power frequency of 210 MHz.

A great advantage of choosing the capacitance of the electrode assembly 126 in this manner, and then matching

30 the resultant electrode-plasma resonant frequency and the source power frequency, is that resonance of the electrode and plasma near the source power frequency provides a wider impedance match and wider process window, and consequently much greater immunity to changes in process

35 conditions, and therefore greater performance stability.

14

The entire processing system is rendered less sensitive to variations in operating conditions, e.g., shifts in plasma impedance, and therefore more reliable along with a greater range of process applicability. As will be

5   discussed later in the specification, this advantage is further enhanced by the small offset between the electrode-plasma resonant frequency and the source power frequency.

10 Why the Plasma Has a Negative Capacitance:
        The capacitance of the plasma is governed by the electrical permittivity of the plasma, ε, which is a complex number and is a function of the electrical permittivity of free space ε_0, the plasma electron frequency

15 ω_{pe}, the source power frequency ω and the electron-neutral collision frequency ν_{en} in accordance with the following equation:
$$\varepsilon = \varepsilon_0[1-\omega_{pe}^2/(\omega(\omega+i\nu_{en}))] \text{ where } i = (-1)^{1/2}.$$
        (The plasma electron frequency ω_{pe} is a simple function

20 of the plasma electron density and is defined in well-known publications on plasma processing.)
        In one working example, the neutral species was Argon, the plasma electron frequency was about 230 MHz, the RF source power frequency was about 210 MHz with chamber

25 pressure in the range of 10 mT to 200 mT with sufficient RF power applied so that the plasma density was between 10^9 and 10^{12} cc^{-1}. Under these conditions, which are typical of those favorable to plasma etch processes, the plasma generally has a negative capacitance because its effective

30 electrical permittivity defined by the foregoing equation is negative. Under these conditions, the plasma had a negative capacitance of -50 to -400 pico farads. Then as we have seen above in more general terms, the plasma capacitance, as a function of plasma electron density (as

15

well as source power frequency and electron-neutral
collision frequency) tends to be generally limited by
favored plasma process realities for key applications such
as dielectric etch, metal etch and CVD, to certain desired
5   ranges, and to have a negative value at VHF source power
frequencies. By exploiting these characteristics of the
plasma, the electrode capacitance matching and frequency-
matching features of the invention achieve a process
window capability and flexibility and stability of
10   operation not previously possible.

Impedance Transformation Provided by the Stub 135:

    The stub 135 provides an impedance transformation
between the 50 Ω output impedance of the RF generator 150
15   and the load impedance presented by the combination of the
electrode assembly 126 and the plasma within the chamber.
For such an impedance match, there must be little or no
reflection of RF power at the generator-stub connection and
at the stub-electrode connection (at least no reflection
20   exceeding the VSWR limits of the RF generator 150). How
this is accomplished will now be described.

    At the desired VHF frequency of the generator 150 and
at a plasma density and chamber pressure favorable for
plasma etch processes (i.e., $10^9 - 10^{12}$ ions/cm^3 and 10 mT -
25   200 mT, respectively), the impedance of the plasma itself
is about $(0.3 + (i)7)\Omega$, where 0.3 is the real part of the
plasma impedance, $i=(-1)^{1/2}$, and 7 is the imaginary part of
the plasma impedance. The load impedance presented by the
electrode-plasma combination is a function of this plasma
30   impedance and of the capacitance of the electrode
assembly126. As described above, the capacitance of the
electrode assembly 126 is selected to achieve a resonance
between the electrode assembly 126 and the plasma with an
electrode-plasma resonant frequency of about 200 MHz.
35   Reflections of RF power at the stub-electrode interface are

16

minimized or avoided because the resonant frequency of the
stub 135 is set to be at or near the electrode-plasma
resonant frequency so that the two at least nearly resonate
together.

5   At the same time, reflections of RF power at the
generator-stub interface are minimized or avoided because
the location of the tap 160 along the axial length of the
stub 135 is such that, at the tap 160, the ratio of the
standing wave voltage to the standing wave current in the
10   stub 135 is near the output impedance of the generator 150
or characteristic impedance of the cable 162 (both being
about 50 Ω). How the tap 160 is located to achieve this
will now be discussed.

15   Axial Location of the Stub's Tap 160:
         The axial length of the coaxial stub 135 preferably is
a multiple of a quarter wavelength of a "stub" frequency
(e.g., 220 MHz) which, as stated above, is near the
electrode-plasma resonant frequency. In the preferred
20   embodiment, this multiple is two, so that the coaxial stub
length is about a half-wavelength of the "stub" frequency,
or about 29 inches.

         The tap 160 is at a particular axial location along
the length of the stub 135. At this location, the ratio
25   between the amplitudes of the standing wave voltage and the
standing wave current of an RF signal at the output
frequency of the generator 150 corresponds to an input
impedance matching the output impedance of the RF generator
150 (e.g., 50 Ohms). This is illustrated in FIGS. 2A and
30   2B, in which the voltage and current standing waves in the
stub 135 have a null and a peak, respectively, at the
shorted outer stub end 135a. A desired location for the
tap 160 is at a distance A inwardly from the shorted end,
where the ratio of the standing wave voltage and current
35   corresponds to 50 Ohms. This location is readily found by

17

the skilled worker by empirically determining where the
standing wave ratio is 50 Ohms. The distance or location A
of the tap 160 that provides a match to the RF generator
output impedance (50 Ω) is a function of the characteristic

5   impedance of the stub 135, as will be described later in
this specification. When the tap 160 is located precisely
at the distance A, the impedance match space accomodates a
9:1 change in the real part of the load impedance, if the
RF generator is of the typical kind that can maintain

10 constant delivered power over a 3:1 voltage standing wave
ratio (VSWR).

In the preferred embodiment, the impedance match space
is greatly expanded to accommodate a nearly 60:1 change in
the real part of the load impedance. This dramatic result

15 is achieved by slightly shifting the tap 160 from the
precise 50 Ω point at location A toward the shorted
external end 135a of the coaxial stub 135. This shift is
preferably 5% of a wavelength in the preferred embodiment
(i.e., about 1.5 inch). It is a discovery of the invention

20 that at this slightly shifted tap location, the RF current
contribution at the tap 160 subtracts or adds to the
current in the stub, which ever becomes appropriate, to
compensate for fluctuations in the plasma load impedance,
as will be described below with reference to FIGS. 3 and 4.

25 This compensation is sufficient to increase the match space
from one that accomodates a 9:1 swing in the real part of
the load impedance to a 60:1 swing.

It is felt that this behavior is due to a tendency of
the phase of the standing wave current in the stub 135 to

30 become more sensitive to an impedance mismatch with the
electrode-plasma load impedance, as the tap point is moved
away from the "match" location at A. As described above,
the electrode assembly 126 is matched to the negative
capacitance of the plasma under nominal operating

35 conditions. This capacitance is -50 to -400 pico farads at

18

the preferred VHF source power frequency (210 MHz). At
this capacitance the plasma exhibits a plasma impedance of
$(.3 +i7)\Omega$. Thus, $.3\Omega$ is the real part of the plasma
impedance for which the system is tuned.   As plasma
5 conditions fluctuate, the plasma capacitance and impedance
fluctuate away from their nominal values. As the plasma
capacitance fluctuates from that to which the electrode 125
was matched, the phase of the electrode-plasma resonance
changes, which affects the phase of the current in the stub
10 135. As the phase of the stub's standing wave current thus
shifts, the RF generator current supplied to the tap 160
will either add to or subtract from the stub standing wave
current, depending upon the direction of the phase shift.
The displacement of the tap 160 from the 50 Ω location at A
15 is limited to a small fraction of the wavelength (e.g.,
5%).

     FIG. 3 illustrates the standing wave current in the
stub 135 when the real part of the plasma impedance has
increased due to plasma fluctuations. In FIG. 3, the
20 current standing wave amplitude is plotted as a function of
axial location along the stub 135. A discontinuity in the
standing wave current amplitude at the location 0.1 on the
horizontal axis corresponds to the position of the tap 160.
In the graph of FIG. 3, an impedance mismatch occurs
25 because the real part of the plasma impedance is high,
above the nominal plasma impedance for which the system is
tuned (i.e., at which the electrode capacitance matches the
negative plasma capacitance). In this case, the current at
the tap 160 subtracts from the standing wave current in the
30 stub 135. This subtraction causes the discontinuity or
null in the graph of FIG. 3, and reduces the delivered
power to offset the increased load. This avoids a
corresponding increase in delivered power (I^2R), due to the
higher load (R).

19

FIG. 4 illustrates the standing wave current in the stub 135 when the real part of the plasma impedance decreases. In FIG. 4, the current standing wave amplitude is plotted as a function of axial location along the stub

5   135. A discontinuity in the standing wave current amplitude at the location 0.1 marks the position of the tap 160. In the graph of FIG. 4, the real part of the plasma impedance is low, below the nominal plasma impedance for which the system is tuned. In this case, the current at

10   the tap 160 adds to the standing wave current in the stub 135. This addition increases the delivered power to offset the decreased load, to avoid a concomitant decrease in delivered power, I^2R, due to the decreased load, R. With such compensation, much greater changes in load impedance

15   can be accommodated so that the match space in increased significantly.

This expansion of the match space to accommodate a 60:1 swing in the real part of the load impedance enhances process window and reliability of the reactor. This is

20   because as operating conditions shift during a particular process or application, or as the reactor is operated with different operating recipes for different applications, the plasma impedance will change, particularly the real part of the impedance. In the prior art, such a change could

25   readily exceed the range of the conventional match circuit employed in the system, so that the delivered power could no longer be controlled sufficiently to support a viable process, and the process could fail. In the present invention, the range of the real part of the load impedance

30   over which delivered power can be maintained at a desired level has been increased so much that changes in plasma impedance, which formerly would have led to a process failure, have little or no effect on a reactor embodying this aspect of the invention. Thus, the invention enables

35   the reactor to withstand far greater changes in operating

20

conditions during a particular process or application. Alternatively, it enables the reactor to be used in many different applications involving a wider range of process conditions, a significant advantage.

5   As a further advantage, the coaxial stub 135 that provides this broadened impedance match is a simple passive device with no "moving parts" such as a variable capacitor/servo or a variable frequency/servo typical of conventional impedance match apparatus. It is thus

10   inexpensive and far more reliable than the impedance match apparatus that it replaces.

De-Tuning the Operating and Resonant Frequencies to Broaden the Process Window:

15   In accordance with a further aspect of the preferred embodiment, the system Q is reduced to broaden the process window by slightly offsetting the stub resonant frequency, the electrode-plasma resonant frequency and the plasma source power frequency from one another. As described

20   above, the stub resonant frequency is that frequency at which the axial length of the stub 135 is a half wavelength, and the electrode-plasma resonant frequency is the frequency at which the electrode assembly 126 and the plasma resonate together. In the preferred embodiment, the

25   stub 135 was cut to a length at which its resonant frequency was 220 MHz, the RF source power generator 150 was selected to operate at 210 MHz and the resulting electrode-plasma resonant frequency was about 200 MHz.

        By choosing three such differing frequencies for

30   plasma resonance, stub resonance and source power frequency, rather than the same frequency for all three, the system has been somewhat "de-tuned". It therefore has a lower "Q". The use of the higher VHF source power frequency proportionately decreases the Q as well (in

35   addition to facilitating the match of the electrode and

21

plasma capacitances under etch-favorable operating
conditions).

   Decreasing system Q broadens the impedance match space
of the system, so that its performance is not as
5   susceptible to changes in plasma conditions or deviations
from manufacturing tolerances. For example, the electrode-
plasma resonance may fluctuate due to fluctuations in
plasma conditions. With a smaller Q, the resonance between
the stub 135 and the electrode-plasma combination that is
10 necessary for an impedance match (as described previously
in this specification) changes less for a given change in
the plasma-electrode resonance. As a result, fluctuations
in plasma conditions have less effect on the impedance
match. Specifically, a given deviation in plasma operating
15 conditions produces a smaller increase in VSWR at the
output of RF generator 150. Thus, the reactor may be
operated in a wider window of plasma process conditions
(pressure, source power level, source power frequency,
plasma density, etc). Moreover, manufacturing tolerances
20 may be relaxed to save cost and a more uniform performance
among reactors of the same model design is achieved, a
significant advantage. A related advantage is that the
same reactor may have a sufficiently wide process window to
be useful for operating different process recipes and
25 different applications, such as metal etch, dielectric etch
and/or chemical vapor deposition.

Minimizing the Stub Characteristic Impedance to Broaden the
Process Window:
30   Another choice that broadens the tuning space or
decreases the system Q is to decrease the characteristic
impedance of the stub 135. However, the stub
characteristic impedance preferably exceeds the generator
output impedance, to preserve adequate match space.
35 Therefore, in the preferred embodiment, the system Q is

22

preferably reduced, but only to the extent of reducing the
amount by which the characteristic impedance of the stub
135 exceeds the output impedance of the signal generator
150.

5   The characteristic impedance of the coaxial stub 135
is a function of the radii of the inner and outer
conductors 140, 145 and of the dielectric constant of the
insulator 147 therebetween. The stub characteristic
impedance is chosen to provide the requisite impedance
10   transformation between the output impedance of the plasma
power source 150 and the input impedance at the electrode
135. This characteristic impedance lies between a minimum
characteristic impedance and a maximum characteristic
impedance. Changing the characteristic impedance of the
15   stub 135 changes the waveforms of FIG. 2 and therefore
changes the desired location of the tap 160 (i.e., its
displacement, A, from the far end of the stub 135). The
allowable minimum characteristic impedance of the stub 135
is the one at which the distance A of FIG. 2 is zero so
20   that tap 160 would have to be located on the far end 135a
of the coaxial stub 135 opposite the electrode 125 in order
to see a 50 Ohm ratio between the standing wave current and
voltage. The allowable maximum characteristic impedance of
the stub 135 is the one at which the distance A of FIG. 2
25   is equal to the length of the stub 135 so that the tap 160
would have to be located at the near end 135b of the
coaxial stub 135 adjacent the electrode 125 in order to see
a 50 Ohm ratio between the standing wave current and
voltage.

30   In an initial preferred embodiment, the coaxial stub
characteristic impedance was chosen to be greater (by about
30%) than the output impedance of the RF generator 150, in
order to provide an adequate match space. The stub
impedance must exceed the RF generator output impedance

23

because the impedance match condition is achieved by
selecting the location of the tap point 160 to satisfy

$$Z_{gen} = \alpha^2 [Z_{stub}^2 / r_{plasma}]$$

where α is determined by the location of the tap point and

5   varies between zero and one. (α corresponds to the ratio
of the inductance of the small portion of the stub 135
between the far end 135b and the tap 160 to the inductance
of the entire stub 135.) Since α cannot exceed one, the
stub characteristic impedance must exceed the generator

10   output impedance in order to find a solution to the
foregoing equation. However, since the Q of the system is
directly proportional to the stub characteristic impedance,
the amount by which the stub characteristic impedance
exceeds the generator output impedance preferably is

15   somewhat minimized to keep the Q as low as practical. In
the exemplary embodiment, the stub characteristic impedance
exceeds the generator output impedance by only about 15 Ω.

         However, in other embodiments, the coaxial stub
characteristic impedance may be chosen to be less than the

20   plasma power source (generator) output impedance to achieve
greater power efficiency with some reduction in impedance
match.

Increased Power Efficiency Provided by the Impedance

25   Transformation of the Stub:

         As discussed earlier in this specification, plasma
operating conditions (e.g., plasma density) that favor
plasma etch processes result in a plasma impedance that has
a very small real (resistive) part (e.g., less .3 Ohm) and

30   a small imaginary (reactive) part (e.g., 7. Ohms).
Capacitive losses predominate in the combination electrode-
plasma area of the system, because the electrode
capacitance is the predominant impedance to power flow in
that part of the reactor. Therefore, power loss in the

24

electrode-plasma combination is proportional to the voltage
on the electrode-plasma combination. In contrast,
inductive and resistive losses predominate in the stub 135,
because the inductance and resistance of the stub 135 are

5   the predominant elements of impedance to power flow in the
stub 135. Therefore, power loss in the stub 135 is
proportional to current in the stub. The stub
characteristic impedance is much greater than the real part
of the impedance presented by the electrode-plasma

10   combination. Therefore, in the higher impedance stub 135
the voltage will be higher and the current lower than in
the lower impedance plasma in which the current will be
higher and the voltage lower. Thus, the impedance
transformation between the stub 135 and the plasma-

15   electrode combination produces a higher voltage and lower
current in the stub 135 (where resistive and inductive
losses dominate and where these are now minimized) and a
correspondingly lower voltage and higher current at the
plasma/electrode (where capacitive losses dominate and

20   where these are now minimized). In this manner overall
power loss in the system is minimized so that power
efficiency is greatly improved, a significant advantage.
In the preferred embodiment, power efficiency is about 95%
or greater.

25   Thus, the stub 135, configured as described above in
accordance with the invention, serves not only to provide
an impedance match or transformation between the generator
and the electrode-plasma impedances across a very wide
range or window of operating conditions, but in addition

30   provides a significant improvement in power efficiency.

Cross-Grounding:
     The ion energy at the wafer surface can be controlled
independently of the plasma density/overhead electrode
35   power. Such independent control of the ion energy is

25

achieved by applying an HF frequency bias power source to
the wafer. This frequency, (typically 13.56 MHz) is
significantly lower than the VHF power applied to the
overhead electrode that governs plasma density. Bias power

5   is applied to the wafer by a bias power HF signal generator
200 coupled through a conventional impedance match circuit
210 to the wafer support 105. The power level of the bias
generator 200 controls the ion energy near the wafer
surface, and is generally a fraction of the power level of

10   the plasma source power generator 150.

As referred to above, the coaxial stub 135 includes a
shorting conductor 165 at the outer stub end providing a
short circuit between the inner and outer coaxial stub
conductors 140, 145. The shorting conductor 165

15   establishes the location of the VHF standing wave current
peak and the VHF standing wave voltage null as in FIG. 2.
However, the shorting conductor 165 does not short out the
VHF applied power, because of the coupling of the stub
resonance and the plasma/electrode resonance, both of which

20   are at or near the VHF source power frequency. The
conductor 165 does appear as a direct short to ground for
other frequencies, however, such as the HF bias power
source (from the HF bias generator 200) applied to the
wafer. It also shorts out higher frequencies such as

25   harmonics of the VHF source power frequency generated in
the plasma sheath.

The combination of the wafer and wafer support 205,
the HF impedance match circuit 210 and the HF bias power
source 200 connected thereto provides a very low impedance

30   or near short to ground for the VHF power applied to the
overhead electrode. As a result, the system is cross-
grounded, the HF bias signal being returned to ground
through the overhead electrode 125 and the shorted coaxial
stub 135, and the VHF power signal on the overhead

35   electrode 135 being returned to ground through a very low

26

impedance path (for VHF) through the wafer, the HF bias impedance match 210 and the HF bias power generator 200.

The exposed portion of the chamber side wall between the plane of the wafer and the plane of the overhead

5   electrode 125 plays little or no role as a direct return path for the VHF power applied to the overhead electrode 125 because of the large area of the electrode 125 and the relatively short electrode-to-wafer gap. In fact, the side wall of the chamber may be isolated from the plasma using

10 magnetic isolation or a dielectric coating or an annular dielectric insert or removable liner.

In order to confine current flow of the VHF plasma source power emanating from the overhead electrode 125 within the vertical electrode-to-pedestal pathway and away

15 from other parts of the chamber 100 such as the sidewall, the effective ground or return electrode area in the plane of the wafer 110 is enlarged beyond the physical area of the wafer or wafer support 105, so that it exceeds the area of the overhead electrode 125. This is achieved by the

20 provision of the annular semiconductor ring 115 generally coplanar with and surrounding the wafer 110. The semiconductor ring 115 provides a stray capacitance to the grounded chamber body and thereby extends the effective radius of the "return" electrode in the plane of the wafer

25 110 for the VHF power signal from the overhead electrode. The semiconductor ring 115 is insulated from the grounded chamber body by the dielectric ring 120. The thickness and dielectric constant of the ring 120 is selected to achieve a desirable ratio of VHF ground currents through the wafer

30 110 and through the semiconductor ring 115. In a preferred embodiment, the dielectric ring 120 was quartz, having a dielectric constant of 4 9 and was of a thickness of 10 mm.

In order to confine current flow from the HF plasma bias power from the bias generator 200 within the vertical

35 path between the surface of the wafer and the electrode 135

27

and avoid current flow to other parts of the chamber (e.g.,
the sidewall), the overhead electrode 135 provides an
effective HF return electrode area significantly greater
than the area of the wafer or wafer support 105.   The

5   semiconductor ring 115 in the plane of the wafer support
105 does not play a significant role in coupling the HF
bias power into the chamber, so that the effective
electrode area for coupling the HF bias power is
essentially confined to the area of the wafer and wafer

10   support 105.

Enhancement of Plasma Stability:

     In a preferred mode of the invention, plasma stability
was enhanced by eliminating D.C. coupling of the plasma to

15   the shorting conductor 165 connected across the inner and
outer stub conductors 140, 145 at the back of the stub 135.
This is accomplished by the provision of the thin
capacitive ring 180 between the coaxial stub inner
conductor 140 and the electrode 125.   In the embodiment of

20   FIG. 1, the ring 180 is sandwiched between the electrode
125 on the bottom and the conductive annular inner housing
support 176.   Preferably, in the exemplary embodiments
described herein, the capacitive ring 180 had a capacitance
of about 180 picoFarads, depending on the frequency of the

25   bias chosen, about 13 MHz.   With such a value of
capacitance, the capacitive ring 180 does not impede the
cross-grounding feature described above.   In the cross-
grounding feature, the HF bias signal on the wafer pedestal
is returned to the RF return terminal of the HF bias

30   generator 150 via the stub 135 while the VHF source power
signal from the electrode 125 is returned to the RF return
terminal of the VHF source power generator 150 via the
wafer pedestal.
     FIG. 5 is a graph illustrating the reflection

35   coefficient between the VHF power source and the overhead

28

electrode 135 as a function of frequency in a preferred
embodiment of the invention. This graph illustrates the
existence of a very broad band of frequencies over which
the reflection coefficient is below 6 dB, which is
5   indicative of the highly advantageous low system Q
discussed above.

FIG. 6 illustrates the standing wave current (solid
line) and standing wave voltage (dashed line) as a function
of position along the coaxial stub 135 in the case in which
10 the tap 160 is placed at the distance A of FIG. 2B from the
shorted end of the stub.

FIG. 7 illustrates an alternative embodiment of the
invention in which the inner conductor 140 of the coaxial
stub 135 is tapered, having a larger radius at the near
15 stub end 135a adjacent the overhead electrode 125 and a
smaller radius at the far stub end 135b. This feature
provides a transition between a low impedance (e.g., 50 Ω)
presented by the coaxial stub 135 at the tap 160 and a
higher impedance (e.g., 64 Ω) presented by the coaxial stub
20 135 at the overhead electrode 125.

Results:
The invention thus provides a plasma reactor which is
far less sensitive to changes in operating conditions
25 and/or variations in manufacturing tolerances. It is
believed that these great advantages including lack of
sensitivity to operating conditions --i.e., broad tuning or
frequency space for impedance matching-- are the
contributions of a number of reactor features working
30 together in combination, including an overhead reactor
electrode having a capacitance matching or nearly matching
the magnitude of the negative capacitance of the plasma at
the most desired processing plasma ion densities, use of a
VHF source power frequency matching or nearly matching the
35 plasma-electrode resonance frequency; the close

29

relationship of the VHF source power frequency, the plasma-electrode resonance frequency and the stub resonance frequency; offsetting the plasma-electrode resonance frequency, the stub resonance frequency and the source

5   power frequency from one another; and the use of a resonant stub match to couple source power to the overhead electrode, preferably with the source power input tap 160 offset slightly from the ideal match location.

It is believed that offsetting the plasma, stub and

10 source power frequencies broadens the tuning space of the system by, in effect, de-tuning the system. Using a stub match broadens the tuning space by matching across a broader frequency range. Offsetting the stub tap point 160 from the ideal match point further optimizes the system to

15 broaden the tuning space, because this feature has the effect of adding current when delivered power would otherwise decline and of subtracting current when delivered power would otherwise increase. Using a higher (VHF) source power frequency provides a decrease in system Q or

20 an increase in tuning space proportional to the increase in source power frequency. More importantly, this selection allows the electrode-plasma resonance to be matched to the source power frequency at a plasma density favorable to etch processes.

25 Because the invention renders the reactor virtually immune to changes in process conditions over a broader process window, it provides the three-fold advantage of a reactor that is (a) workable over a wider range of process condition deviations, (b) useful over a broader range of

30 applications (different process recipes) and (c) whose performance is virtually unaffected over a wider range of manufacturing tolerances, so that reactor-to-reactor characteristics are uniform.

Consequently, superior results have been attained.

35 Specifically, the Q of the system has been minimized to

<div align="center">30</div>

about 5 in some cases to retain a superior degree of
uniformity of characteristics and performance among
different reactors of the same model, and to enhance
process window. High plasma densities on the order of 10^{12}

5 ions/cc have been achieved consistently with only 2kW of
source power. The system sustained plasmas over a pressure
range of 10 mT to 200 mT with no transitions with source
power levels as low as 10 W. The shorted impedance
matching coaxial stub resonating near the VHF plasma and

10 source power frequencies shorted out parasitic VHF plasma
sheath harmonics while realizing a power efficiency in
excess of 95%. The system accomodated plasma resistive
load variations of 60:1 and reactive load variations of 1.3
to .75 while maintaining the source power SWR at less than

15 3:1.

It is believed that this increased capability to
accommodate load variations, and hence expanded process
windows, is due in large part to (a) the matching of the
electrode and plasma capacitances under the design

20 operating conditions, accomplished as above described by
appropriate choice of dielectric values between the
electrode 125 and its conductive support as well as the
appropriate choice of VHF source power frequency; and (b)
the specially configured coaxial stub with the optimal tap

25 positioning, by which the tap current added to the stub
current under low load conditions and subtracted from it
under high load conditions. It is believed the very high
power efficiency is due in large part to the impedance
transformation provided by the coaxial stub, which

30 minimizes reflection losses both at the generator
connection as well as at the electrode connection, due to
obtaining a match between stub resonant frequency and
electrode-plasma resonant frequency, along with optimal tap
positioning for realizing a low current and high voltage in

35 the coaxial stub where resistive losses dominate and a high

31

current low voltage at the electrode/plasma where capacitive losses dominate. Yet all these benefits are provided while avoiding or minimizing the need for coventional impedance match apparatus.

5   While preferred embodiments of the invention adapted for silicon and metal etch have been described in detail, the invention is also advantageous for choices of plasma operating conditions other than those described above, including different ion densities, different plasma source

10   power levels, different chamber pressures. These variations will produce different plasma capacitances, requiring different electrode capacitances and different electrode-plasma resonant frequencies and therefore require different plasma source power frequencies and stub resonant

15   frequencies from those described above. Also, different wafer diameters and different plasma processes such as chemical vapor deposition may well have different operating regimes for source power and chamber pressure. Yet it is believed that under these various applications, the

20   invention will generally enhance the process window and stability as in the preferred embodiment described above.

       While the invention has been described in detail by reference to preferred embodiments, it is understood that variations and modifications thereof may be made without

25   departing from the true spirit and scope of the invention.

32

What is claimed is:

1.   A plasma reactor for processing a semiconductor workpiece, comprising:

a reactor chamber having a chamber wall and
5   containing a workpiece support for holding the semiconductor workpiece;

an overhead electrode overlying said workpiece support, said electrode comprising a portion of said chamber wall;

10   an RF power generator for supplying power at a frequency of said generator to said overhead electrode and capable of maintaining a plasma within said chamber at a desired plasma ion density level;

said overhead electrode having a reactance that
15   forms a resonance with the plasma at an electrode-plasma resonant frequency which is at or near said frequency of said generator.

2.   The reactor of Claim 1 wherein said plasma has a reactance and the reactance of said electrode corresponds
20   to the reactance of said plasma.

3.   The reactor of Claim 2 wherein the reactance of said electrode is a conjugate of the reactance of said plasma.

4.   The reactor of Claim 2 wherein the reactance of
25   said plasma comprises a negative capacitance, and wherein the capacitance of said electrode is the same magnitude as the magnitude of said negative capacitance of said plasma.

5.   The reactor of Claim 1 wherein the frequency of said RF generator and the electrode-plasma resonant
30   frequency are VHF frequencies.

6.   The reactor of Claim 5 wherein said plasma reactance is a function of said plasma ion density and said plasma ion density supports a selected plasma process of said reactor.

33

7.   The reactor of Claim 6 wherein said plasma process is a plasma etch process and wherein said plasma ion density lies in a range from about 10^9 ions/cubic centimeter to about 10^{12} ions/cubic centimeter.

5   8.   The reactor of Claim 1 further comprising a fixed impedance matching element connected between said generator and said overhead electrode, said fixed impedance match element having a match element resonant frequency.

9.   The reactor of Claim 8 wherein the match element

10   resonant frequency and said electrode-plasma resonant frequency are offset from one another and the frequency of said generator lies between said electrode-plasma resonant frequency and said match element resonant frequency.

10.   The reactor of Claim 9 wherein said frequency of

15   said generator, said plasma frequency and said match element resonant frequency are all VHF frequencies.

11.   The reactor of Claim 8 wherein said fixed impedance match element comprises:

a coaxial stub having a near end thereof adjacent

20   said overhead electrode for coupling power from said RF power generator to said overhead electrode and providing an impedance transformation therebetween, said coaxial stub comprising:

an inner conductor connected at said near

25   end to said overhead electrode,

an outer conductor around and spaced from said inner conductor and connected at said near end to an RF return potential of said RF power generator,

a tap at a selected location along the axial

30   length of said stub, said tap comprising a connection between said inner conductor and an output terminal of said RF power generator.

12.   The reactor of Claim 11 further comprising a shorting conductor connected at a far end of said stub

34

opposite said near end to said inner and outer connectors, whereby said far end of said stub is an electrical short.

13. The reactor of Claim 11 wherein the length of said stub between said near and far ends is equal to a

5   multiple of a quarter wavelength of said match element resonant frequency of the stub.

14. The reactor of Claim 13 wherein said multiple is two whereby said length of said stub is a half-wavelength at said match element resonant frequency.

10   15. The reactor of Claim 13 wherein said frequency of said RF power generator, said match element resonant frequency and said electrode-plasma resonant frequency are all VHF frequencies offset from one another.

16. The reactor of Claim 11 wherein said stub

15   comprises aluminum.

17. The reactor of Claim 11 wherein said selected location is a location along the length of said stub at which a ratio between a standing wave voltage and a standing wave current in said stub is at least nearly equal

20   to an output impedance of said RF power generator.

18. The reactor of Claim 17 wherein said selected location of said tap is shifted from an ideal location at which said ratio is equal to said output impedance, the shift being sufficient to realize an addition of current at

25   said tap whenever the load impedance at said overhead electrode decreases below a nominal level and to realize a subtraction of current at said tap whenever the load impedance at said overhead electrode increases above a nominal level.

30   19. The reactor of Claim 68 wherein the shift from said ideal location is about 5% of one wavelength of the VHF frequency of said RF generator.

20. The reactor of Claim 18 wherein the shift from said ideal location is such that at least a 6:1 increase in

35   resistive match space is realized.

35

21. The reactor of Claim 11 further comprising an insulating material between said inner and outer conductors of said stub, said insulating material having a dielectric constant, said dielectric constant and the radii of said

5 inner and outer conductors being such that said coaxial stub has a characteristic impedance which is greater than the output impedance of said RF power generator.

22. The reactor of Claim 21 wherein said characteristic impedance of said coaxial stub is about 30%

10 greater than the output impedance of said RF power generator.

23. The reactor of Claim 21 wherein said coaxial stub has a characteristic impedance which is less than the output impedance of said RF power generator.

15 24. The reactor of Claim 21 further comprising an insulating seal between said overhead electrode and a remaining portion of said chamber wall, the dielectric constant of said insulating seal and the area of said overhead electrode being such that said plasma in said

20 chamber resonates with said overhead electrode at said electrode-plasma resonant frequency.

25. The reactor of Claim 21 wherein said inner conductor is a tapered cylinder, having a maximum radius at said near end of said stub and a minimum radius at said far

25 end of said stub.

26. The reactor of Claim 21 further comprising an HF frequency bias power generator and an impedance match circuit connected between said HF frequency bias power generator and said wafer support, wherein the frequency of

30 said RF power generator connected to said electrode, said electrode-plasma resonant frequency and said match element resonant frequency are VHF frequencies.

27. The reactor of Claim 26 wherein said wafer support provides an RF return path for VHF power coupled

35 into said chamber from said overhead electrode.

36

28. The reactor of Claim 27 further comprising a semiconductive annular ring surrounding the periphery of said wafer, said ring extending an effective return electrode area presented to VHF power coupled into said
5   chamber from said overhead electrode.

29. The reactor of Claim 28 further comprising an insulating annulus supporting said ring and insulating said ring from said chamber wall, the dielectric constant of said ring determining apportionment of VHF power return
10 current between said wafer support and said semiconductor ring.

30. The reactor of Claim 28 wherein the effective return electrode area for VHF power coupled into said chamber from said overhead electrode exceeds the area of
15 said overhead electrode.

31. The reactor of Claim 30 wherein the combination of said overhead electrode with said coaxial stub provides an RF return path for HF power coupled into said chamber from said wafer support, said overhead electrode having an
20 area greater than the area of said wafer support.

32. The reactor of Claim 28 further comprising a capacitive element between said overhead electrode and said fixed impedance matching element, the capacitive element having a capacitance sufficient to provide DC isolation
25 between said plasma and said fixed impedance matching element.

33. The reactor of Claim 31 wherein said inner conductor of said coaxial stub comprises a hollow conduit, said reactor further comprising:

30   gas inlet apparatus in said overhead ceiling for distributing process gas into said chamber;
        a gas feed line extending through said conduit to said gas inlet apparatus in said overhead ceiling.

34. The reactor of Claim 33 wherein said gas feed
35 line comprises metal.

37.

35. The reactor of Claim 33 wherein said inner conductor of said coaxial stub comprises a hollow conduit, said reactor further comprising:

coolant passages within said overhead ceiling;

a coolant feed line extending through said conduit to said coolant passages in said overhead ceiling.

36. The reactor of Claim 35 wherein said coolant feed line comprises metal.

37. A plasma reactor for processing a semiconductor workpiece, comprising:

a reactor chamber having a chamber wall and containing a workpiece support for holding the semiconductor workpiece;

an overhead electrode overlying said workpiece support, said electrode comprising a portion of said chamber wall;

an RF power generator for supplying power at a frequency of said generator to said overhead electrode and capable of maintaining a plasma within said chamber at a desired plasma ion density level;

said overhead electrode having a capacitance such that said overhead electrode and the plasma formed in said chamber at said desired plasma ion density resonate together at an electrode-plasma responant frequency, said frequency of said generator being at least near said electrode-plasma resonant frequency.

38. The plasma reactor of Claim 37 further comprising a fixed impedance matching element connected between said generator and said overhead electrode, said fixed impedance matching element having a match element resonant frequency.

39. The plasma reactor of Claim 38 wherein said frequency of said generator lies between said electrode-plasma resonant frequency and said match element resonant frequency.

38

40. The plasma reactor of Claim 39 wherein each of said frequencies is a VHF frequency.

41. A plasma reactor for processing a semiconductor workpiece, comprising:

5   a reactor chamber having a chamber wall and containing a workpiece support for holding the semiconductor workpiece;

an overhead electrode overlying said workpiece support, said electrode comprising a portion of said

10   chamber wall;

an RF power generator capable of supplying power to said overhead electrode to maintain a plasma in said chamber at a desired plasma ion density;

a coaxial stub having a near end thereof adjacent

15   said overhead electrode for coupling power from said RF power generator to said overhead electrode and providing an impedance transformation therebetween, said coaxial stub comprising:

an inner conductor connected at said near

20   end to said overhead electrode;

an outer conductor around and spaced from said inner conductor and connected at said near end to an RF return potential of said RF power generator,

a tap at a selected location along the axial

25   length of said stub, said tap comprising a connection between said inner conductor and an output terminal of said RF power generator.

42. The reactor of Claim 41 further comprising a shorting conductor connected at a far end of said stub

30   opposite said near end to said inner and outer connectors, whereby said far end of said stub is an electrical short.

43. The reactor of Claim 42 wherein said stub has a stub resonant frequency, and the length of said stub between said near and far ends is equal to a multiple of a

35   quarter wavelength of stub resonant frequency.

39

44. The reactor of Claim 43 where said multiple is two whereby said length of said stub is a half-wavelength at said stub responant frequency.

45. The reactor of Claim 43 wherein said RF power generator produces a VHF power signal at a VHF frequency, said stub resonant frequency being a VHF frequency offset from the VHF frequency of said generator.

46. The reactor of Claim 45 wherein said overhead electrode has a capacitance such that said electrode and said plasma at said selected plasma ion density resonate together at a VHF electrode-plasma resonant frequency, said VHF frequency of said generator lying between said electrode-plasma resonant frequency and said stub resonant frequency.

47. The reactor of Claim 41 wherein said selected location is a location at which a ratio between standing voltage and current waves in said stub is at least nearly equal to an output impedance of said RF power generator.

48. The reactor of Claim 47 wherein said selected location of said tap is shifted from an ideal location at which said ratio is equal to said output impedance, the shift being sufficient to realize an addition of current at said tap whenever the load impedance at said overhead electrode decreases below a nominal level and to realize a subtraction of current at said tap whenever the load impedance at said overhead electrode increases above a nominal level.

49. The reactor of Claim 48 wherein the shift from said ideal location is about 5% of one wavelength of the stub resonant frequency.

50. The reactor of Claim 48 wherein the shift from said ideal location is such that at least a 6:1 increase in resistive match space is realized.

51. The reactor of Claim 41 further comprising an insulating material between said inner and outer conductors

40

of said stub, said insulating material having a dielectric
constant, said dielectric constant and the radii of said
inner and outer conductors being such that said coaxial
stub has a characteristic impedance which is greater than
5   the output impedance of said RF power generator.

52. The reactor of Claim 51 wherein said
characteristic impedance of said coaxial stub is about 30%
greater than the output impedance of said RF power
generator.

10   53. The reactor of Claim 41 wherein said coaxial stub
has a characteristic impedance which is less than the
output impedance of said RF power generator.

54. The reactor of Claim 41 further comprising an
insulating seal between said overhead electrode and a
15   remaining portion of said chamber wall, the dielectric
constant of said insulating seal and the area of said
overhead electrode being such that the plasma at said
selected plasma ion density and said overhead electrode
resonate together at a VHF electrode-plasma resonant
20   frequency.

55. The reactor of Claim 51 wherein said inner
conductor is a tapered cylinder, having a maximum radius at
said near end of said stub and a minimum radius at said far
end of said stub.

25   56. The reactor of Claim 41 further comprising an HF
frequency bias power generator and an impedance match
circuit connected between said HF frequency bias power
generator and said wafer support.

57. The reactor of Claim 56 wherein said wafer
30   support provides an RF return path for VHF power coupled
into said chamber from said overhead electrode.

58. The reactor of Claim 57 further comprising a
semiconductive annular ring surrounding the periphery of
said wafer, said ring extending an effective return

41

electrode area presented to VHF power coupled into said
chamber from said overhead electrode.

59. The reactor of Claim 58 further comprising an
insulating annulus supporting said ring and insulating said
5　ring from said chamber wall, the dielectric constant of
said ring determining apportionment of VHF power return
current between said wafer support and said semiconductor
ring.

60. The reactor of Claim 58 wherein the effective
10　return electrode area for VHF power coupled into said
chamber from said overhead electrode exceeds the area of
said overhead electrode.

61. The reactor of Claim 60 wherein said overhead
electrode with said coaxial stub provides an RF return path
15　for HF power coupled into said chamber from said wafer
support, said overhead electrode having an area greater
than the area of said wafer support.

62. The reactor of Claim 61 wherein said inner
conductor of said coaxial stub comprises a hollow conduit,
20　said reactor further comprising:

gas inlet apparatus in said overhead ceiling for
distributing process gas into said chamber;

a gas feed line extending through said conduit to
said gas inlet apparatus in said overhead ceiling.

25　63. The reactor of Claim 22 wherein said inner
conductor of said coaxial stub comprises a hollow conduit,
said reactor further comprising:

coolant passages within said overhead ceiling;

a coolant feed line extending through said
30　conduit to said coolant passages in said overhead ceiling.

64. A method of processing a semiconductor wafer in a
plasma reactor chamber, comprising:

providing an overhead electrode having an
electrode capacitance and a VHF power generator;

42

coupling said VHF power generator to said overhead electrode through an impedance matching stub having a length which is a multiple of about one quarter of a VHF stub frequency and connected at one end thereof to

5 said overhead electrode and connected at a tap point therealong to said VHF power generator;

applying an amount of power from said VHF power generator to said overhead electrode to maintain a plasma density at which said plasma and electrode together tend to

10 resonate at a VHF frequency at least near the VHF frequency of said VHF power generator.

65. The method of Claim 64 wherein said plasma density lies in a range of 10^9 through 10^{12} ions per cubic centimeter.

15 66. The method of Claim 64 wherein the step of applying power matches a negative capacitance of the plasma to the capacitance of the electrode.

67. The method of Claim 64 further comprising:

locating said tap at least near an axial location

20 along the length of said stub at which the ratio between the standing wave voltage and standing wave current equals the output impedance of said VHF generator.

68. The method of Claim 67 wherein said locating comprises locating said stub at a position slightly offset

25 from said axial location by an amount which realizes a significant increase in the resistive match space of an impedance match provided by said coaxial stub.

69. The method of Claim 68 wherein said significant increase is on the order of a 6:1 increase.

30 70. The method of Claim 69 wherein said position is offset by about 5% of the wavelength of said VHF generator.

71. The method of Claim 64 wherein the VHF frequency of said VHF generator lies between said plasma VHF frequency and said stub VHF frequency.

43

72.   The method of Claim 64 wherein said multiple is 2 whereby said stub is about a half wavelength at said stub frequency.

73.   A plasma reactor for processing a semiconductor

5   workpiece, comprising:

a reactor chamber having a chamber wall and containing a workpiece support for holding the semiconductor workpiece;

an electrode at least generally facing said

10   workpiece support;

a coaxial stub having a near end thereof adjacent said overhead electrode and comprising:

an inner conductor connected at said near end to said overhead electrode,

15   an outer conductor around and spaced from said inner conductor;

an RF generator connected across said inner and outer conductors.

74.   The reactor of Claim 73 wherein said outer

20   conductor and said wafer support are connected to an RF return potential of said RF generator.

75.   The reactor of Claim 74 further comprising a coaxial cable providing the connection between said coaxial stub and said RF generator, said coaxial cable having a

25   center conductor connected at one end to an RF output terminal of said RF generator and connected at an opposite end to said electrode, said coaxial cable further having an outer conductor connected at one end to an RF return potential of said RF generator and coupled at an opposite

30   end to said portions of said chamber electrically connected to said wafer support.

76.   The reactor of Claim 75 wherein said cable has a characteristic impedance equal to the output impedance of said RF generator.

44

77. The reactor of Claim 76 wherein the connection between said inner conductors of said coaxial stub and coaxial cable is at a tap point along the length of said coaxial stub at which the ratio of the standing wave

5   voltage and current in said stub is at least approximately equal to said characteristic impedance of said cable.

78. The reactor of Claim 77 wherein the connection between said inner conductors of said coaxial stub and coaxial cable is a tap point slightly offset from a

10 location along the length of said coaxial stub at which the ratio of the standing wave voltage and current in said stub at frequency of said RF generator is equal to said characteristic impedance of said cable.

79. The reactor of Claim 78 wherein said tap point is

15 offset from said location by about 5% of a wavelength at the frequency of said RF generator.

80. The reactor of Claim 73 further comprising a shorting conductor connected between said inner and outer conductors at a far end of said stub away from said

20 electrode.

81. The reactor of Claim 80 wherein the length of said stub between said near and far ends is equal to a multiple of a quarter wavelength of a stub resonant frequency at least near the frequency of said RF generator.

25   82 The reactor of Claim 81 where said multiple is two whereby said length of said stub is a half-wavelength at said stub resonant frequency.

83. The reactor of Claim 81 wherein said RF power generator produces a VHF power signal at a VHF frequency,

30 said stub resonant frequency being a VHF frequency offset from the VHF frequency of said generator.

84. The reactor of Claim 83 wherein said overhead electrode and the plasma formed in said chamber resonate together at a VHF electrode-plasma resonant frequency, said

35 VHF frequency of said generator lying between said

45

electrode-plasma resonant frequency and said stub resoant frequency.

85. The reactor of Claim 73 further comprising an insulating material between said inner and outer conductors of said stub, said insulating material having a dielectric constant, said dielectric constant and the radii of said inner and outer conductors being such that said coaxial stub has a characteristic impedance which is greater than the output impedance of said RF power generator.

86. The reactor of Claim 73 wherein said coaxial stub has a characteristic impedance which is less than the output impedance of said RF power generator.

87. The reactor of Claim 73 wherein said inner conductor of said coaxial stub comprises a hollow conduit, said reactor further comprising:

gas inlet apparatus in said overhead ceiling for distributing process gas into said chamber;

a gas feed line extending through said conduit to said gas inlet apparatus in said overhead ceiling.

88. The reactor of Claim 73 wherein said inner conductor of said coaxial stub comprises a hollow conduit, said reactor further comprising:

coolant passages within said overhead ceiling;

a coolant feed line extending through said conduit to said coolant passages in said overhead ceiling.

89. A method of providing an impedance transformation between the output impedance of an RF generator output and a load impedance at an electrode of a plasma reactor for processing a semiconductor wafer, comprising:

providing a fixed coaxial stub and connecting said fixed coaxial stub between said RF generator output and said electrode.

90. The method of Claim 89 wherein providing a fixed coaxial stub comprises providing a fixed coaxial stub

46

having a characteristic impedance different from said output impedance of said RF generator.

91. The method of Claim 89 further comprising operating said RF generator at a power level that maintains

5 a plasma in said reactor with a plasma ion density at which the combination of said plasma and said electrode tend to resonate near the output frequency of said RF generator.

92. The method of Claim 91 wherein said density is in the range of 10^9 to 10^{12} ions per cubic centimeter and the

10 frequency of said RF generator is a VHF frequency.

93. The method of Claim 89 wherein connecting said fixed stub comprises connecting said RF generator output to said stub at a tap point at least near a location along the length of said stub between the ends thereof at which the

15 ratio standing wave voltage and current is equal to the output impedance of said RF generator.

94. The method of Claim 93 wherein said tap point is shifted from said location by a fraction of a wavelength at

47

FIG. 1

FIG. 2A

100 VOLTS

2 AMPS

0.01λ

A

FIG 2B

3/4

FIG. 3

FIG. 4

FIG. 5

$dBrho_j$

FIG. 6

FIG. 7